


# Action Lists






By default, a new Automise project has one Action List called Default. This default Action List cannot be deleted or moved. When a project starts, the first enabled action in the Default Action List is executed. If any action fails, will cause the build process to halt with an error. To perform cleanup tasks when the project fails for any reason wrapping the actions to protect in a try..catch..end is recommended.

Welcome Switch - Case Actions.atp5			
Description	Enabled	Ignore Failure	Status
FTP Connect [ SydneyServer ]	<input checked="" type="checkbox"/>	<input type="checkbox"/>	
Try	<input checked="" type="checkbox"/>		
FTP Upload [ SydneyServer ] [ *.do...	<input checked="" type="checkbox"/>	<input type="checkbox"/>	
Finally	<input checked="" type="checkbox"/>		
FTP Disconnect [ SydneyServer ]	<input checked="" type="checkbox"/>	<input type="checkbox"/>	
End	<input checked="" type="checkbox"/>		
Default Upload			

 You can drag actions from one Action List to another by dragging them over the Action List tab, then dropping them on the other Action List.

## Adding Action List

You can Add, Delete, Rename or re-order extra Action Lists from the Project menu, or by right clicking on the Action List headings:

	Add Action List...
	Rename Action List...
	Move Action List Left
	Move Action List Right
<hr/>	
View Start Action List      Ctrl+Alt+M	
Goto Last Action List      Ctrl+Alt+BkSp	
<hr/>	
Action List Configuration...	
<hr/>	
	Delete Action List

To run a specific Action List, add a "Run Action List" action to the calling Action List, then set the Action List property of that action.

## See Also

[Automise Variables](#) | [Action Lists Parameters](#)